



MODEL **SM-4242** | Specification Sheet  
Residential Series • Brass & Copper • Step Light

TYPE:  MODEL:

PROJECT:

**PRODUCT FEATURES**



Wattage	3 W
Voltage	9 – 15 VAC
Housing	Brass
Dimensions	5" L x 2 7/8" H x 7/8" D

**ORDERING INFORMATION**

EXAMPLE: **SM-4242-BSO-3-W**

CATEGORY	MODEL	FINISH	LED
SM	4242		

CATEGORY	MODEL	FINISH	LED
<b>SM</b> Surface Mount Step Light	<b>4242</b>	<b>BSO</b> Olde Brass	<b>3-W</b> 3 Watts   Warm   Integrated LED
		<b>B</b> Black	
		<b>DZ</b> Dark Bronze	
		<b>GT</b> Granite	
		<b>W</b> White	
		<b>BR</b> Architectural Brick	
		<b>LZ</b> Light Bronze	
		<b>SB</b> Special Bronze	
		<b>GG</b> Glossy Gray	
		<b>R</b> Rust	
		<b>HG</b> Hunter Green	
		<b>WB</b> Weathered Bronze	
		<b>WI</b> Weathered Iron	
		<b>GM</b> Graphite Metallic	
		<b>G</b> Verde	
<b>P</b> Pewter			
<b>M</b> Mocha			
<b>OF</b> Olde Finish			



PROFESSIONAL  
OUTDOOR LIGHTING

www.VistaPro.com • email@vistapro.com • Fax: (888) 670-VISTA (8478)  
1625 Surveyor Avenue • Simi Valley, CA 93063 • (805) 527-0987 • (800) 766-VISTA (8478)

Vista Professional Outdoor Lighting reserves the right to modify the design and/or construction of the fixture shown without further notification.



### SPECIFICATIONS

**HOUSING CONSTRUCTION:**

Die-cast solid brass.

**FINISH:**

Olde Brass.  
Optional powder coat finish available in Black, Architectural Bronze, Dark Bronze, Granite, White, Architectural Brick, Light Bronze, Special Bronze, Glossy Gray, Rust, Hunter Green, Weathered Bronze, Weathered Iron, Graphite Metallic, Verde, Pewter, Mocha and Olde Finish.

**LENS:**

Translucent, high-impact polycarbonate lens.

**MOUNTING:**

Recessed mounting box included.

**FASTENERS:**

All fasteners are stainless steel.

**WIRING:**

Prewired with a 36" pigtail of 18-2 direct-burial cable and underground connectors.

**CERTIFICATION:**

UL Listed to U.S. and Canadian safety standards for low voltage landscape luminaires (UL 1838).

**LED:**

Integrated LED Module. 3 Watts.

**ELECTRICAL:**

Input voltage range 9 - 15 VAC.  
Low voltage transformer required to operate (sold separately).

### DIMENSIONS

